

CP-4-150

VHF 75 MHz 150 Watts Single Cavity Band Pass Filter

- For use in repeaters and full duplex radios.
- Single cavity
- Easy tuning.

ELECTRICAL SPECIFICATIONS

Type	VHF Low - Single Cavity Band Pass Filter
Frequency	66-88 MHz
Maximum Input Power	150 Watts
Insertion loss	0.5 - 2.0 dB
Attenuation	See diagram
VSWR	≤ 1:1.5
Impedance	50 Ohm
Frequency Stability	9 ppm/°C (approx.)



MECHANICAL SPECIFICATIONS

Color	Black Grey (RAL7021)
Dimension	15 x 15 x 120 cm + tuning screw
Weight	10 kg
Operating Temperature	-30°C to +60°C
Connector	Type N-female
Serial no.	On product label

ORDERING INFORMATION

CP-4-AQ	Not tuned In Box
---------	---------------------

